RX-A1060 AV Receiver AVENTAGE





























































*Streaming service availability depends on regions.





Standby Power Consumption

HDMI Control off, Standby Through off	0.1 W
HDMI Standby Through on	1.4 W
Network Standby on	2.1 W (wired)

Dimensions (W x H x D)

435 x 182 x 439 mm (with antenna up: 435 x 247 x 439 mm) 17-1/8" x 7-1/8" x 17-1/4" (with antenna up: 17-1/8" x 9-3/4" x 17-1/4")

Weight

14.9 kg; 32.8 lbs.

Innuta

inputs		
HDMI*1 (Audio Input Assignable*2, HDMI1-7:HDCP2.2 compatible)	8	
Network (Ethernet / Wi-Fi)	1 / 1	
USB*1	1	
Radio Antenna (FM/AM)	1/1	
Optical Digital	3	
Coaxial Digital	3	
Analogue Audio*1 (with Phono)	9	
Component Video (Audio Input Assignable)	3	
Composite Video*1	5	

Outputs

Outputo	
HDMI (HDCP2.2 compatible)	2 (Zone assignable)
Component Video Monitor	1
Composite Monitor	1
Pre Out	7.2ch
Speaker*3/*4	7 ch / 9 ter
Subwoofer	2 x mono
Headphone Jack*1	1

Otners		
Zone 2 Audio Out with Volume and Tone Controls	1	
Remote In/Out	1/1	
+12V / Total 0.1A Trigger Out	2	
RS-232C	1	
Terminal for Detachable Power Cable	1	

- *1 Including front panel terminals.
 *2 Front HDMI input is not assignable.
- *3 Assignable for surround back L/R to Zone 2. *4 Assignable for front presence L/R to bi-amp (front L/R) or Zone 2.

RX-A1060 AV Receiver NENTAGE



Main Features

- Dolby Atmos[®] and DTS:X[™] support
- AVENTAGE AV Receivers: Designed to Deliver the Highest Levels of Audio Performance
- Aluminium Front Panel Offers Visual and Aural Benefits
- Anti Resonance Technology (A.R.T.) Wedge helps to ensure that vibrations do not affect sound quality
- Symmetrical Power Amp Layout and Rigid chassis with additional bottom frames
- · Professional quality digital audio by ESS DAC
- 7-channel powerful surround sound
- 110 W per channel (8 ohms, 20 Hz-20 kHz, 0.06 % THD, 2 ch driven)
- 165 W per channel (8 ohms, 1 kHz, 10 % THD, 1 ch driven)
- MusicCast for audio enjoyment in every room
- Wi-Fi Built-in and Wireless Direct Compatible for Easy Network
- Bluetooth® for wireless music streaming and Compressed Music Enhancer for Bluetooth®
- AirPlay, Napster®*, Spotify®*, JUKE* music streaming service and AV Controller app *Music service availability varies by region.
- DSD 2.8MHz / 5.6MHz direct playback, FLAC / WAV / AIFF 192kHz / 24bit, Apple Lossless 96kHz / 24-bit playback
- HDMI® (8 in / 2 out) 4K Ultra HD Full Support with 4K60p (4:4:4), HDCP2.2 (7 in / 2 out), HDR Video and BT.2020 pass-through
- YPAO™ R.S.C. (Reflected Sound Control) sound optimisation with multi-point measurement
- YPAO™ Volume to ensure natural sounds even at low volume
- Virtual Surround Back Speaker for playing 7.1-channel content with a 5.1-channel system
- HDMI[®] Zone Switching allows different HD audio / video sources playback in different rooms
- Zone Extra Bass for more powerful bass sound in another room (Zone 2)
- Zone Volume Equalizer for optimum sound balance in another room (Zone 2)
- Detachable AC power cord for easier installation
- ECO mode operation for about 20% less power consumption

Features

RX-A1060 AV Receiver NENTAGE

Audio Features

- 9-channel powerful surround sound
 110 W per channel (8 ohms, 20 Hz-20 kHz, 0.06 % THD, 2 ch driven)
 165 W per channel (8 ohms, 1 kHz, 10 % THD, 1 ch driven)
- Dolby Atmos[®] and DTS:X[™] support
- · Symmetrical power amplifier layout
- Heat sink with anti-vibration and anti-therma properties
- Rigid chassis with additional bottom frames
- Two ESS SABRE™9006A 8-channel DACs featuring true professional digital audio quality
- High speed thermal feedback power amplifi er
- High quality Volume IC and Independent Pure Power Supply
- Ultra Low jitter PLL circuitry helps optimise sound imaging
- Extra 5th foot with Anti-Resonance Technology (A.R.T. Wedge) to reduce Vibration
- High Resolution Music Enhancer further heightens musicality from the original content
- H-shaped Cross Frame for additional chassis rigidity
- DSD 2.8MHz / 5.6MHz direct playback
- FLAC or WAV 192kHz/24-bit audio playback
- · Apple Lossless audio playback
- Compressed Music Enhancer for Bluetooth®
- Phono input for vinyl playback Bluetooth®
- Phono input for vinyl playback

Video Features

- HDMI[®] (8 in / 2 out) 4K Ultra HD Full Support with 4K60p (4:4:4), HDCP2.2 (7 in / 2 out), HDR Video and BT.2020 pass-through
- 4K video upscaling from analogue and HDMI® input
- Supports Deep Colour (30 / 36 bit), x.v.Colour, 24 Hz Refresh Rate and Auto Lip-Sync compensation
- Yamaha original video processing that optimises processing for each type of video content
- -Motion adaptive and edge adaptive deinterlacing
- -Multi-cadence (incl. 3-2 pull-down) detection
- -Resolution enhancement (detail and edge enhancement)
- -Video signal control (Contrast,
- Brightness, Saturation

Advanced Features

- MusicCast for audio enjoyment in every room
- Bluetooth® for wireless music streaming (SBC / AAC)
 Network functions
- Wi-Fi Built-in (802.11b/a/n)
- Easy Wi-Fi setup i.e. iOS Wi-Fi settings sharing, WPS etc.
- AirPlay® allows music streaming from Mac, PC, iPod, iPhone, iPad
- AV Controller app for operating various functions from iOS or Android smartphones and tablets
- Access to: Internet Radio (vTuner): MP3, WMA

Streaming Services (Napster®*, Spotify®*, Pandora®*, JUKE®*)

*Music service availability varies by region.

Music files on PC / NAS: WAV, MP3, WMA, AAC, FLAC, Apple Lossless, AIFF, DSD

- -DLNA® 1.5 certified
- Gapless playback compatibility allows play without interruption
- Front panel USB Digital Connection for USB thumbdrives

- Advanced GUI on-screen display with HD capability
- YPAO™ R.S.C. (Reflected Sound Control) sound optimisation with multi-point measurement
- Background Video feature (for Radio / USB / Bluetooth® /AUDIO / NET / AUX input)
- SCENE PLUS simple and versatile functionality
- HDMI® CEC powers up compatible TVs and Blu-ray Disc™ players
- 12 SCENE choices (4 on front panel and others on GUI)
- Zone SCENE 4 SCENE buttons for Zone 2
- Versatile parameters can be stored into each SCENE

Advanced HDMI® Zone Switching allows various

Versatile Zone Control

- Pre-out terminal for Zone 2 with volume control
- Advanced HDMI® Zone Switching allows various input sources to be output via HDMI® and enjoyed in different rooms
- · Zone 2 on/off and control on front panel
- Zone GUI (song / station selection, album cover art display)
- System Backup / Recovery function
- Zone mono, Zone volume, Zone tone controls, Zone balance and Zone audio delay
- · Party mode

Surround Realism

- Rear presence channel support for maximum 3D sound effect
- HD Audio decoding with CINEMA DSP 3D (23 DSP programmes)
- Compressed Music Enhancer with CINEMA DSP
- Dialogue Lift ensures that dialogue comes from the centre of the screen
- Dialogue Level Adjustment for proper sound balance with dialogue and vocals
- Virtual Presence Speaker function for CINEMA DSP 3D surround without Front Presence Speakers
- Virtual CINEMA FRONT provides virtual surround sound with 5 speakers in front
- Virtual Surround Back Speaker for playing 7.1channel content with a 5.1-channel system
- YPAO™ Volume to ensure natural sounds even at low volume.
- Zone Extra Bass for more powerful bass sound in another room (Zone 2)
- Zone Volume Equalizer for optimum sound balance in another room (Zone 2)
- Extra Bass enriches the powerful bass sound even with small speakers
- SILENT CINEMA to enjoy surround sound with headphone

Eco-Friendly Design

- ECO mode operation for about 20%* less power consumption
- *Compared to power consumption when ECO mode is off (Yamaha measurement)
- Low standby power consumption of 0.1W
- Auto power standby function with variable time setting