

Specifications

NEW PRODUCT INFORMATION



Black



Silver

Network Receiver

R-N402



*Streaming service availability depends on regions.
*DAB compatibility varies by region.

Multi Network Enjoyment

- MusicCast expands entertainment possibilities
- MusicCast CONTROLLER lets you operate from your smartphone or tablet
- Streaming services* offer a huge range of listening choices
* Service availability depends on region
- FM tuner have 40 station preset memories
- Wireless music streaming via *Bluetooth*® or AirPlay®
- *Bluetooth*® Output for convenient music streaming
- USB digital connection for USB devices
- FLAC or WAV 192kHz / 24-bit audio playback
- Gapless Playback compatibility

High Quality Sound

- 85W + 85W (8ohms, 40Hz – 20kHz, 0.2% THD)
- 125W + 125W (8ohms, 1kHz, 10% THD)
- Yamaha high sound quality, created by rich experience and tradition, and high technological expertise (Traditional Natural Sound concept / high sound quality circuit design)
- 5.6MHz DSD Native and AIFF 192kHz / 24-bit reproduction with high performance 24-bit D/A converter
- Digital audio input for TV or Blu-ray player

Elegant Appearance, Energy-saving Convenience

- Simple yet sophisticated design
- Auto Power Standby
- Screw-type speaker terminals
- Speaker selector and speaker terminals for two systems

Power Output

85 W + 85 W (8 ohms, 40Hz - 20kHz, 0.2% THD)

125 W + 125 W (8 ohms, 1kHz, 10% THD)

Network Functions

LAN DLNA ver. 1.5 (DMP/DMR), Wi-Fi

Bluetooth: (Version) Ver.2.1+EDR, (Profile) A2DP, AVRCP, (Audio codec) Sink: SBC, AAC, Source: SBC

Supported Format

MP3, WMA, MPEG4 AAC: 32 to 48 kHz 16/24bit

WAV, FLAC, AIFF: 32 to 192 kHz 16/24bit

ALAC: 32 to 96 kHz 16/24bit

DSD: 2.8 / 5.6 MHz

Terminals

Input

Analogue Audio (CD, LINE 1, LINE 2, LINE 3) 4

Optical Digital 1

Coaxial Digital 1

USB 1

Output

Analogue Audio (LINE 1) 1

Speaker 2 (4 terminals)

Headphone Kack 1

Radio Antenna (FM / AM) 1/1

Dimension (W x H x D)

435 x 141 x 333 mm

Weight

7.3 kg